

alarm Receiver unit
DAR-241



Features

- o 20CH Alarm Receiver Unit (Rack Type)
- o Used for Mid-sized Security System, such as Matrix System, PC Control System
- o Alarm activated and checked during absence with Memory LED by Channel
- o Built-in Speaker - Alarm Output
- o Alarm can be released only by manual
- o TTL,RS-485/232 Port supported : can be connected to PC, MATRIX
- o Graphic Output

Specifications

MODEL	DAR-241
Sensor input	20CH
Sensor type	Active High(N/C)
Graphic	20 CH (Open Collector)
Line output	Relay Output
Alarm line	Siren Output
Others oupput	Status of Channel On/Off, Alarm On/Off
Control function	Alarm On/Off Control, Siren, Channel, Line
Communication	RS-232, RS-485
Communication speed	1200, E, 8, 1 or 9600, N, 8, 1
Power supply	12V DC
Power consumption	Max. 10W
Operating Temp	0℃~ +40℃
Weight	Approx. 3.5kg
Dimensions	430(W) x 44(H) x 350(D)mm

Dimensions

